7 Electrical Parts List

❋ You can search for updated part codes through CMS web site.
URL : http://ecms. samsungelectronics. com/

7-1-1 GY17CS* Main PCB Parts

Loc. No.	Code No.	Description	Specification	Remarks
-	BN94-00484B	ASSY PCB MAIN	GY17CS	
CIS1	0202-001044	SOLDER-WIRE.	S63S-W3.0,S63S,D3,63Sn/37Pb,-	SNA
CIS2	0202-001222	SOLDER-WIRE FLUX	RS-107,RS60-1.2AA,D1.2,SN60/PB40,-	SNA
CIS3	0204-001095	THINNER	#4520,-,-,-	SNA
CIS4	0204-001677	FLUX	DF-201TVS,MIX,0.820,FLUX 13%,G	SNA
CIS6	BN39-00408A	LEAD CONNECTOR	GY17VS,UL1061#28,UL/CSA,8P/7P,170MM,#28,12505HS-08,12505HS-07,BK,SJ03-01-154,TAP	
CIS7	BN61-00161A	GUIDE-POWER	GH17PS,ABS PC,-	SNA
CN101	3711-004712	CONNECTOR-HEADER	BOX,9P,1R,2mm,STRAIGHT,SN	
CN102	3701-001219	CONNECTOR-DSUB	15P,3R,FEMALE,ANGLE,AUF	
PI/PCB+SH/D_SUB	6003-000117	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA
-	BN97-00245B	ASSY SMD	GY17CS	SNA
BD102	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
BD105	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
C101	2203-001402	C-CER,CHIP	220nF,+80-20%,16V,Y5V,TP,1608	
C102	2203-001402	C-CER,CHIP	220nF,+80-20%,16V,Y5V,TP,1608	
C103	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C104	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C105	2402-000179	C-AL,SMD	47uF,20%,16V,GP,TP,6.6x6.6x5.4	
C106	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C107	2402-000179	C-AL,SMD	47uF,20%,16V,GP,TP,6.6x6.6x5.4	
C108	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C109	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C110	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C111	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C112	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C113	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C114	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C115	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C116	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C117	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C118	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C119	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C120	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C121	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C122	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C125	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C126	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C127	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C128	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C129	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C130	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C131	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C132	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C133	2402-000179	C-AL,SMD	47uF,20%,16V,GP,TP,6.6x6.6x5.4	
C134	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C135	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C136	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C137	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C138	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C139	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C140	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C141	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	

Loc. No.	Code No.	Description	Specification	Remarks
C142	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C143	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C144	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C145	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C146	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C147	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C148	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C149	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C150	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C152	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C153	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C154	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C155	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C156	2203-000440	C-CER,CHIP	1nF,10%,50V,X7R,TP,1608,-	
C157	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C158	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C159	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C161	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C162	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C163	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C164	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C165	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C166	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C167	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C169	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
C170	2203-000440	C-CER,CHIP	1nF,10%,50V,X7R,TP,1608,-	
C201	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C202	2203-000189	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	
C203	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C204	2203-000236	C-CER,CHIP	0.1NF,5%,50V,C0G,TP,1608	
C205	2203-000998	C-CER,CHIP	0.047NF,5%,50V,C0G,TP,1608	
C206	2203-000236	C-CER,CHIP	0.1NF,5%,50V,C0G,TP,1608	
C207	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C208	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C209	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C210	2203-002099	C-CER,CHIP	0.0068nF,0.25pF,50V,NP0,TP,1608	
C211	2203-002099	C-CER,CHIP	0.0068nF,0.25pF,50V,NP0,TP,1608	
C212	2203-002099	C-CER,CHIP	0.0068nF,0.25pF,50V,NP0,TP,1608	
C214	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C215	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C302	2203-000626	C-CER,CHIP	0.022NF,5%,50V,C0G,TP,1608	
C303	2203-000626	C-CER,CHIP	0.022NF,5%,50V,C0G,TP,1608	
C304	2203-000384	C-CER,CHIP	0.015NF,5%,50V,C0G,TP,1608	
C305	2203-000384	C-CER,CHIP	0.015NF,5%,50V,C0G,TP,1608	
C309	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C310	2203-000626	C-CER,CHIP	0.022NF,5%,50V,C0G,TP,1608	
C311	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C312	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C313	2203-000626	C-CER,CHIP	0.022NF,5%,50V,C0G,TP,1608	
C316	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C317	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C318	2203-000257	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	
C319	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C401	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C402	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C403	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C404	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C405	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	

Loc. No.	Code No.	Description	Specification	Remarks
C406	2203-001652	C-CER,CHIP	470nF,+80-20%,16V,Y5V,TP,1608	
C407	2402-001042	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	
C408	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C409	2203-001652	C-CER,CHIP	470nF,+80-20%,16V,Y5V,TP,1608	
C410	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C411	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C412	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C413	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C414	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C415	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C421	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
CIS5	0202-001162	SOLDER-CREAM	RMA-20-21L,S63,-,SN63/PB36.6/AG0.4,FLUX9.5%	SNA
CN103	3711-002127	CONNECTOR-HEADER	BOX,8P,1R,1.25mm,SMD-A,SN	
CN401	3711-004070	CONNECTOR-HEADER	BOX,30P,1R,1.25mm,SMD-A,SN	
D101	0403-001435	DIODE-ZENER	QZX363C5V6,5.32-5.88,200MW,SOT-363,TP	
D102	0403-001435	DIODE-ZENER	QZX363C5V6,5.32-5.88,200MW,SOT-363,TP	
D201	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D202	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D203	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D204	0401-001056	DIODE-SWITCHING	MMBD4148SE,75V,200MA,SOT-23,TP	
D205	0401-001056	DIODE-SWITCHING	MMBD4148SE,75V,200MA,SOT-23,TP	
D206	0401-001056	DIODE-SWITCHING	MMBD4148SE,75V,200MA,SOT-23,TP	
D207	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D208	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D209	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D210	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D211	0401-001056	DIODE-SWITCHING	MMBD4148SE,75V,200MA,SOT-23,TP	
D212	0403-000258	DIODE-ZENER	BZX84C5V6,5.6V,5.2-6.0V,225mW,	
IC101	0505-001376	FET-SILICON	FDC6329L,N/P,8V,2.5A,-,0.7W,SC-74	
IC102	1203-002842	IC-VOLTAGE REGULATOR	AP1117D-33A,TO-252,3P,6.7X5.6MM,PLASTIC,3.235/3.365V,-,0TO+150C,1A,-,TP	
IC103	1203-002974	IC-POSI.FIXED REG.	AP1117D-25A,TO-252,3P,6.7X5.6MM,PLASTIC,2.45/2.55V,-,0TO+150C,1A,-,TP	
IC201	0803-000117	IC-TTL	74F14,INVERTER,SOP,14P,150MIL,	
IC202	1103-000129	IC-EEPROM	24C02,256x8BIT,SOP,8P,150MIL,1	
IC301_SOCK	3704-000249	SOCKET-IC	32P,PLCC,SN,1.27mm	
IC302	1103-001023	IC-EEPROM	524C80D81,1028x8Bit,SOP,8P,150MIL,10mS,5V,10%,PLASTIC,0to+70C,110uA,CMOS,TP	
IC303	1003-001611	IC-LCD CONTROLLER	RTD2020,PQFP,208P,28X28MM,-,-,TR,PLASTIC,3.3V,0TO+70C,-,-,-	
IC401	1205-002412	IC-TRANSMITTER	DTC34LM85A,TSSOP,56P,14x6.1mm,PLASTIC,3.3V,1.4W,0to+70C,TP,LVDS TRANSMITTER	
IC402	1205-002412	IC-TRANSMITTER	DTC34LM85A,TSSOP,56P,14x6.1mm,PLASTIC,3.3V,1.4W,0to+70C,TP,LVDS TRANSMITTER	
IC403	1203-002997	IC-VOL. DETECTOR	ELM7529CBA-S,SOT-23,3P,1.5x2.9x1.1mm,PLASTIC,-0.3/+0.3V,200mW,-65to+150C,1.4mA,-	
L102	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L103	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L104	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L105	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L106	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L107	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L201	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L401	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L402	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L404	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L406	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
MP1.0	BN41-00349A	PCB MAIN	GY17CS,FR-4,2,MP1.0,1.6T,125*110,2	SNA
Q101	0501-000342	TR-SMALL SIGNAL	KSC1623-Y,NPN,200mW,SOT-23,TP,135-270	
R101	2007-000084	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	
R102	2007-000078	R-CHIP	1Kohm,5%,1/10W,TP,1608	
R103	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R105	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R109	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R111	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	

Loc. No.	Code No.	Description	Specification	Remarks
R112	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R113	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R115	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R117	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R118	2007-000078	R-CHIP	1Kohm,5%,1/10W,TP,1608	
R119	2007-000078	R-CHIP	1Kohm,5%,1/10W,TP,1608	
R120	2007-001167	R-CHIP	75ohm,5%,1/10W,TP,1608	
R121	2007-000078	R-CHIP	1Kohm,5%,1/10W,TP,1608	
R122	2007-000078	R-CHIP	1Kohm,5%,1/10W,TP,1608	
R140	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R142	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R203	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R204	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R205	2007-001167	R-CHIP	75ohm,5%,1/10W,TP,1608	
R206	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R207	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R208	3301-000314	BEAD-SMD	120ohm,1.6x0.8x0.8mm,150mA,TP,FERRITE,0.2ohm	SNA
R209	2007-000123	R-CHIP	1.5Kohm,5%,1/10W,TP,1608	
R210	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R211	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R212	2007-000084	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	
R213	2007-000084	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	
R215	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R216	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R217	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R218	3301-001236	CORE-FERRITE BEAD	AB,60ohm,1.6x0.8x0.8mm,200mA,TP,H,0.7ohm	
R219	3301-001236	CORE-FERRITE BEAD	AB,60ohm,1.6x0.8x0.8mm,200mA,TP,H,0.7ohm	
R221	3301-001236	CORE-FERRITE BEAD	AB,60ohm,1.6x0.8x0.8mm,200mA,TP,H,0.7ohm	
R222	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R223	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R224	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R225	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R226	2007-000078	R-CHIP	1Kohm,5%,1/10W,TP,1608	
R251	2007-000113	R-CHIP	33ohm,5%,1/10W,TP,1608	
R252	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R260	2007-000123	R-CHIP	1.5Kohm,5%,1/10W,TP,1608	
R290	2007-000120	R-CHIP	680ohm,5%,1/10W,TP,1608	
R301	2007-000113	R-CHIP	33ohm,5%,1/10W,TP,1608	
R302	2007-001167	R-CHIP	75ohm,5%,1/10W,TP,1608	
R303	2007-001167	R-CHIP	75ohm,5%,1/10W,TP,1608	
R304	2007-001167	R-CHIP	75ohm,5%,1/10W,TP,1608	
R305	2007-001167	R-CHIP	75ohm,5%,1/10W,TP,1608	
R306	2007-000113	R-CHIP	33ohm,5%,1/10W,TP,1608	
R307	2007-000113	R-CHIP	33ohm,5%,1/10W,TP,1608	
R308	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R309	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R312	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R313	2007-000109	R-CHIP	1Mohm,5%,1/10W,TP,1608	
R314	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R315	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R316	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R317	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R320	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R321	2007-000078	R-CHIP	1Kohm,5%,1/10W,TP,1608	
R322	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R323	2007-000084	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	
R324	2007-000084	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	
R325	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	

Loc. No.	Code No.	Description	Specification	Remarks
R326	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R401	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R402	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R403	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R404	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R405	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R406	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R407	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R408	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R409	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R410	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R411	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R412	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R413	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R414	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R415	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R416	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R417	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R418	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R419	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R420	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R421	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R422	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R423	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R424	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R425	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R426	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R427	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R428	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R429	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
RA301	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA302	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA303	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA304	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA305	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA306	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA307	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA308	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA309	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA310	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA311	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA312	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
X301	2801-003326	CRYSTAL-SMD	24MHz,30ppm,28-ABX,16pF,50ohm,	
MICOM	BN97-00335C	ASSY MICOM	GY17CS	
IC301	1107-001456	IC-FLASH MEMORY	Pm39LV010-70JC,128Kx8Bit,PLCC,32P,11.51x14.05mm,70ns,3V,2.7-3.6V,-,0to+70C,-,-,-	
CIS	BN82-00104K	A/S MICOM	GY17CS	SNA
-	BN94-00443L	ASSY PCB POWER	GY17CS	
C601	2301-001244	C-FILM,MPEF	150nF,20%,275Vac,TP,18x8.5x15,	
C602	2301-001244	C-FILM,MPEF	150nF,20%,275Vac,TP,18x8.5x15,	
C605	2401-003921	C-AL	100uF,20%,400V,WT,BK,18x31.5mm,7.5	
C620	2401-003624	C-AL	470uF,20%,25V,HR,TP,10x16mm,5	
C621	2201-002157	C-CERAMIC,DISC	0.005nF,0.5pF,3000V,SL,TP,7x5.5mm,7.5	
C622	2201-002157	C-CERAMIC,DISC	0.005nF,0.5pF,3000V,SL,TP,7x5.5mm,7.5	
C623	2201-002157	C-CERAMIC,DISC	0.005nF,0.5pF,3000V,SL,TP,7x5.5mm,7.5	
C624	2201-002157	C-CERAMIC,DISC	0.005nF,0.5pF,3000V,SL,TP,7x5.5mm,7.5	
CIS01	0202-000008	SOLDER-WIRE	S63S-W3.0,S63S,D3,63Sn/37Pb,-	SNA

Loc. No.	Code No.	Description	Specification	Remarks
CIS02	0204-001527	FLUX	DF-201TVS,MIX,0.820,FLUX 13%, 14KG	SNA
CIS03	0202-000187	SOLDER-WIRE FLUX	-,RS60S,D1.2,63Sn/37Pb	SNA
CIS04	0204-000442	SOLVENT	1M-1000,C3H70H,96,-	SNA
CIS05	0201-001096	ADHESIVE-HM	#3748,YEL,8500CPS,-	SNA
CN601	BN39-00425A	LEAD CONNECTOR	GY17CS,UL1007#18,UL/CSA,1P,60mm,#18,ST-01T-BCK9,YPT-018S,BK	
CN603	BN39-00415A	LEAD CONNECTOR	GOYA2025,UL1007#24,UL/CSA,9P,90MM,#24,SMH200-09,YBNH200-09,BK	SNA
CN604	3711-005411	CONNECTOR-HEADER	NOWALL,2P,1R,8.5MM,ANGLE,SN,WHT	
CN605	3711-005411	CONNECTOR-HEADER	NOWALL,2P,1R,8.5MM,ANGLE,SN,WHT	
CN606	3711-005411	CONNECTOR-HEADER	NOWALL,2P,1R,8.5MM,ANGLE,SN,WHT	
CN607	3711-005411	CONNECTOR-HEADER	NOWALL,2P,1R,8.5MM,ANGLE,SN,WHT	
D601	0402-001407	DIODE-BRIDGE	G2SB60,600V,1.5A,SIP-4,BK	
IC601	1203-002958	IC-PWM CONTROLLER	NCP1200P60,DIP,8P,10.16X6.6MM,PLASTIC,-,550MW,-25TO+125C,110MA,-,ST	
IC602	0604-001018	PHOTO-COUPLER	DAR-TR,63-125%,200mW,DIP-4,ST	
IS601	BN62-00011A	INSULATION-SHEET	GY17CS,PET,T0.25 * 2,152,337,IVORY,V2	SNA
J1	3711-001665	CONNECTOR-HEADER	NOWALL,9P,1R,2.54MM,STRAIGHT,AU15U,BLK	
J2	3711-001561	CONNECTOR-HEADER	NOWALL,5P,1R,2.54mm,STRAIGHT,A	
J3	3711-001465	CONNECTOR-HEADER	NOWALL,3P,1R,2.54mm,STRAIGHT,A	
L601	BN29-00003A	FILTER LINE NOISE	LCDM0,UU1116,1.6ohm,36.0mH,20x18x26mm,BK,0.2mH,100&cr[500Vdc],-10° ... ~ 70° ...	SNA
L602	BN29-00004A	FILTER LINE NOISE	GY17CS,T0-0803,0.03ohm,30mH,9.5*8.0*18.0MM,5A,250V,BK,2uH,100Mohm(500V)	SNA
L603	BN27-00018A	COIL CHOKE	AR-0520,GOYA17CS,5uH,+-10,100MOHM,L-81 AR 5*20,15.5t,10x29mm,7.0mm,0.9 PI,BK	
T601	BN26-00012A	TRANS POWER	ER3016,LCDTM,680uH,8Pin,500V,14V/5V,2A/2A,40W,60kHz,FERRITE,ER-3016,0.50 ohm,11.	
T602	BN26-00013A	TRANS-INVETER	TMP90140CT,GY17CS,0.7H,8Pin,12V,1Kohm,50kHz,FERRITE,EFD16.2TP4,175mH	
T603	BN26-00013A	TRANS-INVETER	TMP90140CT,GY17CS,0.7H,8Pin,12V,1Kohm,50kHz,FERRITE,EFD16.2TP4,175mH	
TH601	1404-001020	THERMISTOR-NTC	8ohm,15%,-,17mW/C,BK	
-	BN97-00207L	ASSY AUTO-POWER	GY17CS	SNA
BD601	3301-000011	CORE-FERRITE BEAD	AA,3.5x1.0x5.7mm,1500,2375G	
BD602	3301-000011	CORE-FERRITE BEAD	AA,3.5x1.0x5.7mm,1500,2375G	
BD603	3301-000011	CORE-FERRITE BEAD	AA,3.5x1.0x5.7mm,1500,2375G	
C603	2201-002026	C-CERAMIC,DISC	1NF,20%,400V,Y5P,TP,11X6MM,7.5	
C604	2201-002026	C-CERAMIC,DISC	1NF,20%,400V,Y5P,TP,11X6MM,7.5	
C606	2301-001661	C-FILM,PEF	2.2NF,5%,400V,TP,6X9.5X3.5MM,5	
C607	2401-000970	C-AL	22uF,20%,50V,WT,TP,5x11,5	
C608	2202-000654	C-CERAMIC,MLC-RADIAL	100nF,10%,50V,X7R,TP,5.1x6.6x3.2mm,5	
C609	2201-000146	C-CERAMIC,DISC	0.1NF,5%,50V,SL,TP,5X3.5MM,5	
C610	2301-000016	C-FILM,PEF	22nF,5%,100V,TP,7.2x4.5x9.0mm,	
C611	2201-000288	C-CERAMIC,DISC	1NF,10%,2KV,Y5P,TP,9X5MM,7.5	
C612	2401-003139	C-AL	1000uF,20%,25V,WT,TP,10*20,5mm	
C613	2401-003139	C-AL	1000uF,20%,25V,WT,TP,10*20,5mm	
C614	2201-000551	C-CERAMIC,DISC	0.47NF,10%,1KV,Y5P,TP,6.3X5MM,5	
C615	2401-000142	C-AL	1000uF,20%,16V,WT,TP,10x20,5	
C616	2401-000142	C-AL	1000uF,20%,16V,WT,TP,10x20,5	
C618	2301-000019	C-FILM,PEF	47nF,10%,100V,TP,8.9x5.1x13.5m	
C619	2201-000023	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	
C625	2202-002009	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	
D602	0402-000012	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	
D603	0402-000546	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	
D604	0401-000005	DIODE-SWITCHING	1N4148,100V,200mA,DO-35,TP	
EY601	6042-000002	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
EY602	6042-000002	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
EY603	6042-000002	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
EY604	6042-000002	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
EY605	6042-000002	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
EY606	6042-000002	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
EY607	6042-000002	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
EY608	6042-000002	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
EY609	6042-000002	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
EY610	6042-000002	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA

Loc. No.	Code No.	Description	Specification	Remarks
FH601	3601-001226	FUSE-RADIAL LEAD	250V,3.15A,TIME-LAG,PLASTIC,8.5x8mm	
FH602	3601-001226	FUSE-RADIAL LEAD	250V,3.15A,TIME-LAG,PLASTIC,8.5x8mm	
IC603	1203-000002	IC-POSI.ADJUST REG.	431,TO-92,3P,-,PLASTIC,2.44/2.	
J601	BH39-40305U	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	
J602	BH39-40305U	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	
J603	BH39-40305U	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	
J604	BH39-40305U	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	
J605	BH39-40305U	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	
J606	BH39-40305U	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	
J607	BH39-40305U	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	
J608	BH39-40305U	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	
J609	BH39-40305U	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	
J610	BH39-40305U	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	
J611	BH39-40305U	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	
J612	BH39-40305U	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	
J613	BH39-40305U	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	
J614	BH39-40305U	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	
J615	BH39-40305U	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	
J616	BH39-40305U	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	
J617	BH39-40305U	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	
MP1.0	BN41-00343A	PCB SUB	IP Bd,FR1,1,R1.0,1.6mm,138*156mm,GY17CS,2	SNA
R601	2001-001129	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
R602	2001-001129	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
R603	2003-000654	R-METAL OXIDE(S)	33Kohm,5%,2W,AA,TP,4.3x12mm	
R604	2001-000281	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R605	2003-000855	R-METAL OXIDE(S)	47Kohm,5%,3W,AA,TP,6x16mm	
R606	2001-000281	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R607	2001-000221	R-CARBON	1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R608	2001-000890	R-CARBON	6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R609	2005-000421	R-WIRE WOUND	0.5ohm,5%,1W,AA,TP,4x12mm	
R610	2003-000470	R-METAL OXIDE(S)	10ohm,5%,1W,AF,TP,3.3x9mm	
R611	2001-001117	R-CARBON(S)	2KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
R612	2001-000633	R-CARBON	30KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R614	2001-000723	R-CARBON	4.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R615	2001-000472	R-CARBON	2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R616	2001-000633	R-CARBON	30KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R617	2004-004090	R-METAL	6.49Kohm,1%,1/4W,AA,TP,2.5x6.5	
R618	2004-000001	R-METAL	6.2Kohm,1%,1/4W,AA,TP,2.4x6.4m	
R619	2003-000470	R-METAL OXIDE(S)	10ohm,5%,1W,AF,TP,3.3x9mm	
SCR601	1401-000103	THYRISTOR-SCR	800mA,400V,400V,10A,TO-92	
ZD601	0403-001328	DIODE-ZENER	MTZJ22A,20.15-21.20V,500mW,DO-34,TP	
ZD602	0403-000538	DIODE-ZENER	MTZ16C,16V,15.69-16.51V,500mW,	
ZD603	0403-000509	DIODE-ZENER	MTZJ5.6B,5.6V,5.45-5.73V,500mW	
HS601	BP96-00374A	ASSY HEAT SINK P	BP62-00045A,SCREW+NUT,ST6NK60ZFP,OIL SILICON	SNA
CIS	0205-001027	OIL-SILICON	G746,-,-	SNA
CIS	0505-001768	FET-SILICON	STP6NK60ZFP(031Y,N,600V,6A,1.2OHM,32W,TO-220	
CIS	6003-000335	SCREW-TAPTITE	RH,+,2S,M3,L8,ZPC(YEL),SWRCH18	SNA
CIS	BP62-00045A	HEAT SINK-PS	GY17CS,A1050S,T2.0,6,68	SNA
HS602	BP96-00375A	ASSY HEAT SINK P	BP62-00046A,SCREW+NUT,MBR2045CT,MBRF16100CT,RUBBER SILICON	SNA
CIS	0402-000240	DIODE-RECTIFIER	MBR2045,45V,20A,TO-220,ST	
CIS	0404-001125	DIODE-SCHOTTKY	MBR16100CT,100V,8000MA,TO-220AB,ST	
CIS	6003-000335	SCREW-TAPTITE	RH,+,2S,M3,L8,ZPC(YEL),SWRCH18	SNA
CIS	BN61-00628A	SUPPORT	NB21BS,NYLON66,T2.25,@5.25,NTR,DAWG - 5N	SNA
CIS	BN73-00047B	SILICON/RUBBER	NB21BS,TC1370,17*19*T0.4,@3.65	SNA
CIS	BP62-00046A	HEAT SINK-PS	GY17CS,A1050S,T2.0,37,66	SNA

Loc. No.	Code No.	Description	Specification	Remarks
-	BN94-00499A	ASSY PCB POWER-SUB	GY17CS	
CIS01	0202-000008	SOLDER-WIRE	S63S-W3.0,S63S,D3,63Sn/37Pb,-	SNA
CIS03	0202-000187	SOLDER-WIRE FLUX	-,RS60S,D1.2,63Sn/37Pb	SNA
CIS04	0204-000442	SOLVENT	1M-1000,C3H70H,96,-	SNA
CIS02	0204-001527	FLUX	DF-201TVS,MIX,0.820,FLUX 13%, 14KG	SNA
-	BN97-00337A	ASSY SMD-POWER-SUB	GY17CS	SNA
C1	2203-005261	C-CER,CHIP	1000nF,10%,25V,X7R,TP,3216	
C10	2203-001397	C-CER,CHIP	2.2nF,5%,50V,NP0,TP,1608	
C11	2203-000783	C-CER,CHIP	0.33NF,5%,50V,C0G,TP,1608	
C12	2203-000659	C-CER,CHIP	0.27NF,5%,50V,C0G,TP,1608	
C13	2203-001103	C-CER,CHIP	6.8nF,10%,50V,X7R,TP,1608,-	
C14	2203-001103	C-CER,CHIP	6.8nF,10%,50V,X7R,TP,1608,-	
C15	2203-001103	C-CER,CHIP	6.8nF,10%,50V,X7R,TP,1608,-	
C16	2203-001103	C-CER,CHIP	6.8nF,10%,50V,X7R,TP,1608,-	
C17	2203-005249	C-CER,CHIP	100nF,10%,50V,X7R,TP,1608,-	
C18	2203-005249	C-CER,CHIP	100nF,10%,50V,X7R,TP,1608,-	
C19	2203-001598	C-CER,CHIP	2200nF,+80-20%,16V,Y5V,TP,2012	SNA
C2	2203-005261	C-CER,CHIP	1000nF,10%,25V,X7R,TP,3216	
C20	2203-005249	C-CER,CHIP	100nF,10%,50V,X7R,TP,1608,-	
C21	2203-005249	C-CER,CHIP	100nF,10%,50V,X7R,TP,1608,-	
C22	2203-000257	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	
C23	2203-000257	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	
C24	2203-005249	C-CER,CHIP	100nF,10%,50V,X7R,TP,1608,-	
C25	2203-000257	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	
C26	2203-000257	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	
C3	2203-001652	C-CER,CHIP	470nF,+80-20%,16V,Y5V,TP,1608	
C4	2203-001652	C-CER,CHIP	470nF,+80-20%,16V,Y5V,TP,1608	
C5	2203-005249	C-CER,CHIP	100nF,10%,50V,X7R,TP,1608,-	
C6	2203-005249	C-CER,CHIP	100nF,10%,50V,X7R,TP,1608,-	
C7	2203-005249	C-CER,CHIP	100nF,10%,50V,X7R,TP,1608,-	
C8	2203-005249	C-CER,CHIP	100nF,10%,50V,X7R,TP,1608,-	
C9	2203-001103	C-CER,CHIP	6.8nF,10%,50V,X7R,TP,1608,-	
CB1	2203-001598	C-CER,CHIP	2200nF,+80-20%,16V,Y5V,TP,2012	SNA
CB2	2203-000257	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	
CB3	2203-005249	C-CER,CHIP	100nF,10%,50V,X7R,TP,1608,-	
CB4	2203-005249	C-CER,CHIP	100nF,10%,50V,X7R,TP,1608,-	
CIS05	0202-001167	SOLDER-CREAM	RX3603-2330HO,S45A,PASTE,SN63/PB34/BI3,FLUX 10.5%	
CS1	2203-006333	C-CER,CHIP	10000nF,20%,16V,X5R,TP,3216	SNA
CS2	2203-006333	C-CER,CHIP	10000nF,20%,16V,X5R,TP,3216	SNA
D1	0407-000113	DIODE-ARRAY	BAW56LT1,70V,200mA,CK2-3,SOT-23,TP	
D2	0407-000113	DIODE-ARRAY	BAW56LT1,70V,200mA,CK2-3,SOT-23,TP	
D3	0401-000132	DIODE-SWITCHING	BAV99,70V,715mA,SOT-23,TP	
D4	0401-000132	DIODE-SWITCHING	BAV99,70V,715mA,SOT-23,TP	
D5	0401-000132	DIODE-SWITCHING	BAV99,70V,715mA,SOT-23,TP	
D6	0401-000132	DIODE-SWITCHING	BAV99,70V,715mA,SOT-23,TP	
D7	0401-001099	DIODE-SWITCHING	1N4148WS,75V,150mA,SOD-323,TP	
D8	0401-001099	DIODE-SWITCHING	1N4148WS,75V,150mA,SOD-323,TP	
MP1.0	BN41-00347A	PCB SUB-IP	Power_sub,FR4,2,R1.0,0.8mm,45*27,GY17CS,6	SNA
Q1	0505-001803	FET-SILICON	FDS4935,P,-30V,-7A,0.019ohm,1.6W,SO-8	
Q2	0505-001791	FET-SILICON	NTMD6N03R2,N,30V,6A,0.024ohm,2W,SO-8	
R1	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R10	2007-000103	R-CHIP	120Kohm,5%,1/10W,TP,1608	
R11	2007-000094	R-CHIP	22Kohm,5%,1/10W,TP,1608	
R12	2007-000616	R-CHIP	24Kohm,5%,1/10W,TP,1608	
R13	2007-000084	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	
R14	2007-000999	R-CHIP	510ohm,1%,1/10W,TP,1608	
R16	2007-000084	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	

Loc. No.	Code No.	Description	Specification	Remarks
R17	2007-000094	R-CHIP	22Kohm,5%,1/10W,TP,1608	
R18	2007-000058	R-CHIP	49.9Kohm,1%,1/10W,TP,1608	
R19	2007-000094	R-CHIP	22Kohm,5%,1/10W,TP,1608	
R2	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R20	2007-000134	R-CHIP	33Kohm,5%,1/10W,TP,1608	
R21	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R22	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R23	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R24	2007-000060	R-CHIP	100Kohm,1%,1/10W,TP,1608	
R25	2007-000058	R-CHIP	49.9Kohm,1%,1/10W,TP,1608	
R26	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R27	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R28	2007-000130	R-CHIP	39Kohm,5%,1/10W,TP,1608	
R29	2007-000458	R-CHIP	18Kohm,5%,1/10W,TP,1608	
R3	2007-000060	R-CHIP	100Kohm,1%,1/10W,TP,1608	
R30	2007-000058	R-CHIP	49.9Kohm,1%,1/10W,TP,1608	
R4	2007-000105	R-CHIP	200Kohm,5%,1/10W,TP,1608	
R5	2007-000058	R-CHIP	49.9Kohm,1%,1/10W,TP,1608	
R6	2007-000805	R-CHIP	36Kohm,5%,1/10W,TP,1608	
R7	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R8	2007-000058	R-CHIP	49.9Kohm,1%,1/10W,TP,1608	
R9	2007-000094	R-CHIP	22Kohm,5%,1/10W,TP,1608	
RD1	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
RR1	2007-000060	R-CHIP	100Kohm,1%,1/10W,TP,1608	
RR2	2007-000060	R-CHIP	100Kohm,1%,1/10W,TP,1608	
RR3	2007-000999	R-CHIP	510ohm,1%,1/10W,TP,1608	
RS1	2007-000060	R-CHIP	100Kohm,1%,1/10W,TP,1608	
RS2	2007-000060	R-CHIP	100Kohm,1%,1/10W,TP,1608	
RS3	2007-000999	R-CHIP	510ohm,1%,1/10W,TP,1608	
RS4	2007-000999	R-CHIP	510ohm,1%,1/10W,TP,1608	
RS5	2007-000999	R-CHIP	510ohm,1%,1/10W,TP,1608	
RS6	2007-000999	R-CHIP	510ohm,1%,1/10W,TP,1608	
TR1	0506-001069	TR-ARRAY	MBT3904DW1T1,NPN,DUAL,150mW,SOT-363,TP,100-300	
TR2	0506-001069	TR-ARRAY	MBT3904DW1T1,NPN,DUAL,150mW,SOT-363,TP,100-300	
TR3	0506-001071	TR-ARRAY	MBT3946DW1T1,NPN/PNP,2,150mW,SOT-363,TP,100-300	
TR4	0506-001070	TR-ARRAY	MBT3906DW1T1,NPN,DUAL,150mW,SOT-363,TP,100-300	
TR5	0506-001070	TR-ARRAY	MBT3906DW1T1,NPN,DUAL,150mW,SOT-363,TP,100-300	
TR6	0501-002397	TR-SMALL SIGNAL	MMBT2907AWT1,PNP,150MW,SOT-323,TP,75-	
U1	1203-002400	IC-POWER SUPERVISOR	OZ960,SSOP,20P,154MIL,PLASTIC,-,800MW,-55TO+150C,-,2.5V,TR	
U2	1201-002046	IC-OP AMP	LM324,TSSOP,TP,14P,5x4.4mm,QUAD,-,PLASTIC,5.0V,-,0to+70C,70dB,-,5nA,-90nA,2mV	
ZD1	0403-001411	DIODE-ZENER	-,5.49-5.73V,200MW,SOD-323,TP	
ZD2	0403-001411	DIODE-ZENER	-,5.49-5.73V,200MW,SOD-323,TP	

7-1-2 GY17CS* Others

Loc. No.	Code No.	Description	Specification	Remarks
-	BN90-00432X	ASSY COVER REAR	GY17VSSS/EDC,EDC	SNA
C/R+STD	6003-000337	SCREW-TAPTITE	BH,+,S,M4,L10,ZPC(BLK),SWRCH18	SNA
CIS	BN96-00280B	ASSY COVER P-REAR	GOYA,ABS HB BK07	
CIS	BN61-00377A	BRACKET-VESA	GOYA19(193V),SECC,T1.0	SNA
CIS	BN63-00566B	COVER-REAR	GOYA,ABS HB BK07	SNA
CIS	BN67-00087C	CAP-GATE	GOYA,ABS HB BK07	SNA
-	BN90-00461K	ASSY STAND	GY17VSSS,ADC	SNA
CIS	BN96-00282B	ASSY STAND P	GY17VS,ABS HB BK07	
CIS	6003-000129	SCREW-TAPTITE	BH,+,S,M4,L10,ZPC(YEL),SWRCH18	SNA
CIS	6003-000259	SCREW-TAPTITE	BH,+,B,M3,L8,ZPC(YEL),SWRCH18A	SNA
CIS	6003-000301	SCREW-TAPTITE	BH,+,S,M4,L6,ZPC(YEL),SWRCH18A	SNA
CIS	6003-001185	SCREW-TAPTITE	FH,+,B,M3,L8,NI PLT,SWRCH18A	SNA
CIS	6003-001188	SCREW-TAPTITE	BH,+,B,M4,L10,YEL,SWRCH18A	SNA
CIS	6502-001088	CABLE CLAMP	DAST-1NB,ID9,T1.5,NYLON66,NTR	SNA
CIS	BN61-00326A	BRACKET-STAND	GOYA17(173V),SECC,T2.0	SNA
CIS	BN61-00342A	BRACKET-BASE	GOYA(173V),SECC,T1.2	SNA
CIS	BN63-00567B	COVER-STAND	GOYA,ABS HB BK07	SNA
CIS	BN63-00569B	COVER-STAND	GOYA,ABS HB BK07	SNA
STD	BN73-00049A	RUBBER-FOOT	MO 15,17,19,CR,11*11,60,T1.5,BLK	SNA
CIS	BN96-00284A	ASSY MISC P-HINGE	GOYA17(173V),ZN-2 DIE CASTING	SNA
STD	BN61-00327A	HINGE-BRKT BOTTOM	GOYA17(173V),SK-5 ,T1.5	SNA
STD	BN61-00327B	HINGE-BRKT BOTTOM L	173V,SK-5 ,,T1.5	SNA
STD	BN61-00329A	HINGE-BRKT TOP	GOYA15(153V),ZN-2 DIE CASTING	SNA
-	BN90-00493N	ASSY COVER FRONT	GY17VSSS/XAZ,SEDA	SNA
C/F+C/R	6003-000275	SCREW-TAPTITE	BH,+,B,M3,L10,BLK ,SWCH1018AK	SNA
CIS	BN96-00279E	ASSY COVER P-FRONT	GY17VS(S/M173V),ABS HB GR70,SILVER,TCO99	
CIS	6003-000276	SCREW-TAPTITE	BH,+,B,M3,L10,ZPC(YEL),SWCH10	SNA
CIS	BH68-00035F	LABEL-TCO99	MONITOR,GOYA,PE,T0.05,18.8*16.5,CLEAR	SNA
CIS	BN63-00565B	COVER-FRONT	GY17VS,ABS HB GR70,SILVER	SNA
CIS	BN64-00139B	KNOB POWER-FUNCTION	GY15VS,ABS+ PC 5V,BK07	SNA
CIS	BN67-00074A	LENS-LED	GOYA17(173V),ACRYL,CLEAR	SNA
CIS	BN96-00672A	ASSY BOARD P-FUNCTION	GY17VS,FUNCTION,144*9	SNA
-	BN91-00388F	ASSY LCD-EJ	GH17AS	SNA
CIS	BN07-00071A	LCD	LTM170EU-L01,GH17LS,1280*1024,17,16.19M,56,0.264*0.264,0~55,5.0,TN,-	
-	BN91-00697B	ASSY CHASSIS	GY17CS	
CIS	BN96-00671A	ASSY MISC P-SHIELD SUB	GY17VS,SECC T0.5	SNA
CIS	BN61-00708A	BRACKET-SUPPORT(D_SUB)	GY17VS,SECC,T0.8	SNA
CIS	BN63-00574A	SHIELD-D SUB	GOYA17(173V),SPTE,T0.5	SNA
-	BN91-00724H	ASSY SHIELD	GY17CSSS/EDC	SNA
CIS	BN39-00409A	LEAD CONNECTOR	GY17VS,30AWG*1PR,UL/CSA,30P,135mm,#30,12507HS-30W,1615B-30,BK,CABLE CLAMP	
CIS	BN63-00568B	COVER-STAND	GOYA,ABS HB BK07	SNA
CIS	BN63-00571A	SHIELD-PCB	GOYA17(173V),SPTE,T0.8	SNA
PI/PCB+SH/BRKT	6003-000117	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA
SH/BRKT+PAN	6001-001692	SCREW-MACHINE	BH,+,M3,L3,ZPC(YEL),SWRCH18A,FP,-	
SH/COV+FUN/WIRE	6003-000117	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA
SH/COV+PAN	6001-000131	SCREW-MACHINE	BH,+,M3,L6,ZPC(YEL),SM20C,-	SNA
SH/D_SUB+SH/COV	6003-000269	SCREW-TAPTITE	BH,+,S,M3,L6,ZPC(YEL),SWRCH18A	SNA

Loc. No.	Code No.	Description	Specification	Remarks
SIGNAL	BN39-00244D	CBF SIGNAL	GY15V,15P/15P,20276-N,1830mm,UL20276,BLACK,D-SUB/MALE,W/O CORE,,DET. TYPE	
CIS	BN96-00338A	ASSY MISC P-SHIELD COVER	GOYA173V,,,SECC T1.0	SNA
CIS	BH68-30003B	LABEL-HIGH VOLTAGE	CKA4217(C),ART,100G,YEL,BLK,W30*L30,CDT-TUBE	SNA
CIS	BN61-00709A	BRACKET-SUPPORTI(SHIELD)	GY17VS,SECC,T0.8	SNA
CIS	BN63-00570A	SHIELD-COVER	GOYA17(173V),SECC ,T1.0	SNA
CIS	BN71-00022A	EARTH PLATE	RB15AS,SUS,T0.15	SNA
-	BN92-00724T	ASSY BOX	GY17VSSS/XAZ,SEDA,BRAZIL	SNA
CIS	BH68-00329C	LABEL BAR CODE	-,ALL,TCO99,DOMESTIC,ART-PAPER 90G,-,WHT,BLACK,-,-,-	SNA
CIS	BH75-10529C	UNIT-HANDLE/PACKING	S/M170MP,PE-LD,PE-HD,-,WHITE,-	
CIS	BN72-60001A	LEVER-TOP	LSD210TL,PE-LD,WHITE,TFT_LCD	SNA
CIS	BN72-60002C	LEVER-BOTTOM	S/M170MP,PE-HD,BLUE	SNA
CIS	BN69-00508F	BOX	S/M173V,SILVER,W/W,CB-SW4,WHT,OFFSET,A-1,L448*W442*H176	SNA
-	BN92-00746Z	ASSY ACCESSORY	GY15VSSS/XSE,SEIN,INDONESIA	SNA
CIS	BN96-00476Z	ASSY ACCESSORY	GY15VSSS/XSE,SEIN,INDONESIA	
CIS	0203-000214	TAPE-OPP MASKING	OPP/W50/CLR,T0.05,W50,L400000,	SNA
CIS	6902-000110	BAG PE	LDPE,T0.05,L356,W240,TRP,28,2,PE MARK	SNA
CIS	BH39-10005A	CBF POWER CORD	DET,H05VV-F,250V/10A,IVY,1230M	
CIS	BH68-00522A	MANUAL USERS-00	P/CORD SETUP GUIDE,SYNCMASTER,EN,W/W,MOJO100G,250,250,00	SNA
CIS	BN96-00594A	ASSY MANUAL P-IB+QSG	Goya,SyncMaster,W/W,21Langs,BN59-355A+BH68-376L	SNA
CIS	BH68-00376L	MANUAL-01	LCDQUICK SETUP GUIDE,SYNCMASTER,E/F/S/G/P/I..13LANGS,W/W,MOJO100G,298,420	
CIS	BN59-00355A	S/W DRIVER-USER MANUAL-01	153V,173V,IB/Driver,SyncMaster,W/W,13Langs	SNA
-	BN92-00885V	ASSY P/MATERIAL	GY17CSSS/EDC,EDC,NETHERLANDS	SNA
P/M	0203-001100	TAPE-OPP MASKING	OPP/W75/CLR,T0.05,W75,L800000,CLR	SNA
P/M	6902-000379	BAG AIR	HDPE,T0.2,L1800,W1000,TRP,,,PAPER	SNA
CIS	6902-000522	BAG PE	HDPE/NITRON/HDPE,T0.015/T0.5/T0.015,W700,L800,TRP,28 LANGUAGE,2-	SNA
P/M	BH69-00256A	PAD-PACKING-EDGE	MV540,B400,200,2170,-,-,YEL,-,-	SNA
P/M	BH69-00457A	PACKING-PAD	GH17,FOAM,T3.0,1180,1130	SNA
P/M	BH69-40308A	PALLET-PACKING	GH15LS,WOOD,-,-,W1390,L916,H120,-,-,-	SNA
P/M	BH69-40375A	PAD-TOP	SW4,W900*L830*H4,LXA410TLMU	SNA
P/M	BH69-40379A	PACKING-WRAP	LDPE,W500*T0.02,-,-	SNA
P/M	BN68-00129A	LABEL SHIPPING	-,LABEL SHIPPING,ART-PAPER,100G,-,WHT,BLACK,-,-,-	SNA
P/M	BN69-00140T	PAD-PALLET COVER	SUN(LSA810),SW,900,3760,-,-,-,-,-	SNA
P/M	BN69-00493A	CUSHION-T/B	GY17VS,EPS,,,,,,,M50	SNA
-	BN92-00946S	ASSY LABEL	GY17CSSS/EDC,EDC,NETHERLANDS	SNA
CIS	BN68-00517A	LABEL RATING	GY17CS(GH17LS),SS,PE,T0.05,90X45,BLK,POLYESTER,EDC	SNA
-	ET-GY17CSSS/XSE	2	LTM170EU-L01(ZPD)	-

7-2-1 GY17VS* Main PCB Parts

Loc. No.	Code No.	Description	Specification	Remarks
-	BN94-00496T	ASSY PCB MAIN	GG15LS	
CIS1	0202-001044	SOLDER-WIRE.	"S63S-W3.0,S63S,D3,63Sn/37Pb,-	SNA
CIS2	0202-001222	SOLDER-WIRE FLUX	RS-107,RS60-1.2AA,D1.2,SN60/PB40,-	SNA
CIS3	0204-001095	THINNER	#4520,-,-,-	SNA
CIS4	0204-001677	FLUX	DF-201TVS,MIX,0.820,FLUX 13%,G	SNA
CIS6	BN39-00408A	LEAD CONNECTOR	GY17VS,UL1061#28,UL/CSA,8P/7P,170MM,#28,12505HS-08,12505HS-07,BK,SJ03-01-154,TAP	
CIS7	BN61-00161A	GUIDE-POWER	GH17PS,ABS PC,-	SNA
CN101	3711-004712	CONNECTOR-HEADER	BOX,9P,1R,2mm,STRAIGHT,SN	
CN102	3701-001219	CONNECTOR-DSUB	15P,3R,FEMALE,ANGLE,AUF	
PI/PCB+SH/D_SUB	6003-000117	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA
MICOM	BN97-00224L	ASSY MICOM	GY17VT	
IC301	1107-001456	IC-FLASH MEMORY	Pm39LV010-70JC,128Kx8Bit,PLCC,32P,11.51x14.05mm,70ns,3V,2.7-3.6V,-,0to+70C,-,-,-	
CIS	BN82-00095R	A/S MICOM	GY17VT	SNA
-	BN97-00245A	ASSY SMD	GY17VSP	SNA
BD101	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
BD102	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
BD104	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
BD105	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
C101	2203-001402	C-CER,CHIP	220nF,+80-20%,16V,Y5V,TP,1608	
C102	2203-001402	C-CER,CHIP	220nF,+80-20%,16V,Y5V,TP,1608	
C103	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C104	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C105	2402-000179	C-AL,SMD	47uF,20%,16V,GP,TP,6.6x6.6x5.4	
C106	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C107	2402-000179	C-AL,SMD	47uF,20%,16V,GP,TP,6.6x6.6x5.4	
C108	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C109	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C110	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C111	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C112	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C113	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C114	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C115	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C116	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C117	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C118	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C119	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C120	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C121	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C122	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C125	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C126	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C127	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C128	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C129	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C130	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C131	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C132	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C133	2402-000179	C-AL,SMD	47uF,20%,16V,GP,TP,6.6x6.6x5.4	
C134	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C135	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C136	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C137	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C138	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C139	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C140	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	

Loc. No.	Code No.	Description	Specification	Remarks
C141	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C142	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C143	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C144	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C145	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C146	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C147	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C148	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C149	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C150	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C152	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C153	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C154	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C155	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C157	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C158	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C159	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C161	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C162	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C163	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C164	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C165	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C166	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C167	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C201	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C202	2203-000189	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	
C203	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C204	2203-000236	C-CER,CHIP	0.1NF,5%,50V,C0G,TP,1608	
C205	2203-000626	C-CER,CHIP	0.022NF,5%,50V,C0G,TP,1608	
C206	2203-000236	C-CER,CHIP	0.1NF,5%,50V,C0G,TP,1608	
C207	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C208	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C209	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C210	2203-002099	C-CER,CHIP	0.0068nF,0.25pF,50V,NP0,TP,1608	
C211	2203-002099	C-CER,CHIP	0.0068nF,0.25pF,50V,NP0,TP,1608	
C212	2203-002099	C-CER,CHIP	0.0068nF,0.25pF,50V,NP0,TP,1608	
C214	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C215	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C304	2203-000384	C-CER,CHIP	0.015NF,5%,50V,C0G,TP,1608	
C305	2203-000384	C-CER,CHIP	0.015NF,5%,50V,C0G,TP,1608	
C309	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C310	2203-000626	C-CER,CHIP	0.022NF,5%,50V,C0G,TP,1608	
C311	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C312	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C313	2203-000626	C-CER,CHIP	0.022NF,5%,50V,C0G,TP,1608	
C316	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C317	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C318	2203-000257	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	
C319	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C401	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C402	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C403	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C404	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C405	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C406	2203-001652	C-CER,CHIP	470nF,+80-20%,16V,Y5V,TP,1608	
C407	2402-001042	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	
C408	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C409	2203-001652	C-CER,CHIP	470nF,+80-20%,16V,Y5V,TP,1608	

Loc. No.	Code No.	Description	Specification	Remarks
C410	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C411	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C412	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C413	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C414	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C415	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C420	2402-001042	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	
C421	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
CIS5	0202-001162	SOLDER-CREAM	RMA-20-21L,S63,-,SN63/PB36.6/AG0.4,FLUX9.5%	SNA
CN103	3711-002127	CONNECTOR-HEADER	BOX,8P,1R,1.25mm,SMD-A,SN	
CN401	3711-004070	CONNECTOR-HEADER	BOX,30P,1R,1.25mm,SMD-A,SN	
D101	0403-001435	DIODE-ZENER	QZX363C5V6,5.32-5.88,200MW,SOT-363,TP	
D102	0403-001435	DIODE-ZENER	QZX363C5V6,5.32-5.88,200MW,SOT-363,TP	
D201	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D202	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D203	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D204	0401-001056	DIODE-SWITCHING	MMBD4148SE,75V,200MA,SOT-23,TP	
D205	0401-001056	DIODE-SWITCHING	MMBD4148SE,75V,200MA,SOT-23,TP	
D206	0401-001056	DIODE-SWITCHING	MMBD4148SE,75V,200MA,SOT-23,TP	
D207	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D208	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D209	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D210	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D211	0401-001056	DIODE-SWITCHING	MMBD4148SE,75V,200MA,SOT-23,TP	
D212	0403-000258	DIODE-ZENER	BZX84C5V6,5.6V,5.2-6.0V,225mW,	
IC101	0505-001170	FET-SILICON	SI9933ADY-T1,P,-20V,3.4A,0.06ohm,2W,SO-8	
IC102	1203-002842	IC-VOLTAGE REGULATOR	AP1117D-33A,TO-252,3P,6.7X5.6MM,PLASTIC,3.235/3.365V,-,0TO+150C,1A,-,TP	
IC103	1203-003010	IC-POSI.FIXED REG.	G950,TO-263,3P,10.12x9.15mm,PLASTIC,2.475/2.575,1.6W,0to+125C,1A,-,TP	
IC201	0803-000117	IC-TTL	74F14,INVERTER,SOP,14P,150MIL,	
IC202	1103-000129	IC-EEPROM	24C02,256x8BIT,SOP,8P,150MIL,1	
IC301_SOCK	3704-000249	SOCKET-IC	32P,PLCC,SN,1.27mm	
IC302	1103-001023	IC-EEPROM	524C80D81,1028x8Bit,SOP,8P,150MIL,10mS,5V,10%,PLASTIC,0to+70C,110uA,CMOS,TP	
IC303	1003-001611	IC-LCD CONTROLLER	RTD2020,PQFP,208P,28X28MM,-,-,TR,PLASTIC,3.3V,0TO+70C,-,-,-	
IC401	1205-002309	IC-TRANSMITTER	M385,TSSOP,56P,14x6.1mm,PLASTIC,3.3V,,,TP,LVDS	
IC402	1205-002309	IC-TRANSMITTER	M385,TSSOP,56P,14x6.1mm,PLASTIC,3.3V,,,TP,LVDS	
IC403	1203-002997	IC-VOL. DETECTOR	ELM7529CBA-S,SOT-23,3P,1.5x2.9x1.1mm,PLASTIC,-0.3/+0.3V,200mW,-65to+150C,1.4mA,-	
L101	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L102	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L103	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L104	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L105	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L106	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L107	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L201	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L401	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L402	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L403	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L404	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L405	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L406	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
MP1.0	BN41-00331A	PCB MAIN	GY17VS,FR-4,2,MP1.0,1.6T,125*110mm,2	SNA
Q101	0501-000342	TR-SMALL SIGNAL	KSC1623-Y,NPN,200mW,SOT-23,TP,135-270	
R101	2007-000084	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	
R102	2007-000078	R-CHIP	1Kohm,5%,1/10W,TP,1608	
R103	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R104	2007-000219	R-CHIP	1.2Kohm,1%,1/10W,TP,1608	
R105	2007-000219	R-CHIP	1.2Kohm,1%,1/10W,TP,1608	
R109	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	

Loc. No.	Code No.	Description	Specification	Remarks
R111	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R112	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R113	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R115	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R117	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R118	2007-000078	R-CHIP	1Kohm,5%,1/10W,TP,1608	
R119	2007-000078	R-CHIP	1Kohm,5%,1/10W,TP,1608	
R120	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R121	2007-000078	R-CHIP	1Kohm,5%,1/10W,TP,1608	
R122	2007-000078	R-CHIP	1Kohm,5%,1/10W,TP,1608	
R140	2007-000219	R-CHIP	1.2Kohm,1%,1/10W,TP,1608	
R141	2007-001002	R-CHIP	510ohm,5%,1/10W,TP,1608	
R142	2007-000239	R-CHIP	1.5Kohm,1%,1/10W,TP,1608	
R203	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R204	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R205	2007-001167	R-CHIP	75ohm,5%,1/10W,TP,1608	
R206	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R207	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R208	2007-000113	R-CHIP	33ohm,5%,1/10W,TP,1608	
R209	2007-000123	R-CHIP	1.5Kohm,5%,1/10W,TP,1608	
R210	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R211	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R212	2007-000084	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	
R213	2007-000084	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	
R215	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R216	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R217	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R218	3301-001236	CORE-FERRITE BEAD	AB,60ohm,1.6x0.8x0.8mm,200mA,TP,H,0.7ohm	
R219	3301-001236	CORE-FERRITE BEAD	AB,60ohm,1.6x0.8x0.8mm,200mA,TP,H,0.7ohm	
R221	3301-001236	CORE-FERRITE BEAD	AB,60ohm,1.6x0.8x0.8mm,200mA,TP,H,0.7ohm	
R222	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R223	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R224	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R225	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R226	2007-000078	R-CHIP	1Kohm,5%,1/10W,TP,1608	
R251	2007-000113	R-CHIP	33ohm,5%,1/10W,TP,1608	
R252	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R253	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R260	2007-000078	R-CHIP	1Kohm,5%,1/10W,TP,1608	
R290	2007-000120	R-CHIP	680ohm,5%,1/10W,TP,1608	
R301	2007-000113	R-CHIP	33ohm,5%,1/10W,TP,1608	
R302	2007-001167	R-CHIP	75ohm,5%,1/10W,TP,1608	
R303	2007-001167	R-CHIP	75ohm,5%,1/10W,TP,1608	
R304	2007-001167	R-CHIP	75ohm,5%,1/10W,TP,1608	
R305	2007-001167	R-CHIP	75ohm,5%,1/10W,TP,1608	
R306	2007-000113	R-CHIP	33ohm,5%,1/10W,TP,1608	
R307	2007-000113	R-CHIP	33ohm,5%,1/10W,TP,1608	
R308	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R309	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R312	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R313	2007-000109	R-CHIP	1Mohm,5%,1/10W,TP,1608	
R314	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R315	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R316	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R317	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R320	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R321	2007-000078	R-CHIP	1Kohm,5%,1/10W,TP,1608	
R322	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	

Loc. No.	Code No.	Description	Specification	Remarks
R323	2007-000084	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	
R324	2007-000084	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	
R325	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R326	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R401	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R402	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R403	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R404	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R405	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R406	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R407	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R408	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R409	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R410	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R411	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R412	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R413	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R414	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R415	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R416	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R417	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R418	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R419	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R420	2007-000072	R-CHIP	47ohm,5%,1/10W,TP,1608	
R421	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R422	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R423	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R424	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R425	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R426	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R427	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R428	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R429	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
RA301	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA302	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA303	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA304	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA305	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA306	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA307	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA308	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA309	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA310	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA311	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA312	2011-001410	R-NET	120OHM,5%,1/16W,L,CHIP,8P,TP	
X301	2801-003326	CRYSTAL-SMD	24MHz,30ppm,28-ABX,16pF,50ohm,	

7-2-2 GY17VS* Others

Loc. No.	Code No.	Description	Specification	Remarks
-	BN90-00490A	ASSY COVER FRONT	GY17VS,,,,	SNA
C/F+C/R	6003-001319	SCREW-TAPTITE	BH,+,B,M3,L10,NI PLT,SWRCH18A,-	SNA
C/F	BN96-00279A	ASSY COVER P-FRONT	GOYA17(173V),ABS HB ,WH11	
CIS	6003-000276	SCREW-TAPTITE	BH,+,B,M3,L10,ZPC(YEL),SWCH10	SNA
CIS	BH68-00035F	LABEL-TCO99	MONITOR,GOYA,PE,T0.05,18.8*16.5,CLEAR	SNA
CIS	BN63-00565A	COVER-FRONT	GY17VS,ABS HB,WH11	SNA
CIS	BN64-00139A	KNOB-FUNCTION	GOYA17(173V),ABS PC,GR86	
CIS	BN67-00074A	LENS-LED	GOYA17(173V),ACRYL,CLEAR	SNA
CIS	BN96-00672A	ASSY BOARD P-FUNCTION	GY17VS,FUNCTION,144*9	SNA
-	BN90-00491A	ASSY COVER REAR	GY17VS,,,,	SNA
C/R+STD	6003-000336	SCREW-TAPTITE	BH,+,S,M4,L10,SN PLT,SWRCH18A	
C/R	BN96-00280A	ASSY COVER P-REAR	GOYA17(173V),ABS HB ,GR86	
CIS	BN61-00377A	BRACKET-VESA	GOYA19(193V),SECC,T1.0	SNA
CIS	BN63-00566A	COVER-REAR	GOYA17(173V),ABS HB,GR86	SNA
CIS	BN67-00087A	CAP-GATE	GOYA,ABS HB,,,,GR86,	SNA
-	BN90-00492A	ASSY STAND	GY17VS	SNA
STD	BN96-00282A	ASSY STAND P	GOYA17(173V),ABS HB,WH11	
CIS	6003-000129	SCREW-TAPTITE	BH,+,S,M4,L10,ZPC(YEL),SWRCH18	SNA
CIS	6003-000259	SCREW-TAPTITE	BH,+,B,M3,L8,ZPC(YEL),SWRCH18A	SNA
CIS	6003-000301	SCREW-TAPTITE	BH,+,S,M4,L6,ZPC(YEL),SWRCH18A	SNA
CIS	6003-001185	SCREW-TAPTITE	FH,+,B,M3,L8,NI PLT,SWRCH18A	SNA
CIS	6003-001188	SCREW-TAPTITE	BH,+,B,M4,L10,YEL,SWRCH18A	SNA
CIS	6502-001088	CABLE CLAMP	DAST-1NB,ID9,T1.5,NYLON66,NTR	SNA
CIS	BN61-00326A	BRACKET-STAND	GOYA17(173V),SECC,T2.0	SNA
CIS	BN61-00342A	BRACKET-BASE	GOYA(173V),SECC,T1.2	SNA
CIS	BN63-00567A	COVER-STAND-BODY	GOYA17(173V),ABS HB,WH11	SNA
CIS	BN63-00569A	COVER-STAND-CAP	GOYA17(173V),ABS HB,WH11	SNA
STD	BN73-00049A	RUBBER-FOOT	MO 15,17,19,CR,11*11,60,T1.5,BLK	SNA
CIS	BN96-00284A	ASSY MISC P-HINGE	GOYA17(173V),ZN-2 DIE CASTING	SNA
STD	BN61-00327A	HINGE-BRKT BOTTOM	GOYA17(173V),SK-5 ,T1.5	SNA
STD	BN61-00327B	HINGE-BRKT BOTTOM L	173V,SK-5 ,,T1.5	SNA
STD	BN61-00329A	HINGE-BRKT TOP	GOYA15(153V),ZN-2 DIE CASTING	SNA
-	BN91-00598E	ASSY LCD	GH17AS	SNA
CIS	BN07-00096A	LCD	HT17E12,GH17LS,6BIT FRC,383.3*306.2*22.8,16.7M,-,0.297*0.297,-,5.0V,HDI/ LVDS	
-	BN91-00628Y	ASSY SHIELD	GY17VSSW/XSJ	SNA
CIS	0203-001311	TAPE-CONDUCTOR	DK-K102-90-50,T0.13,W50,L90,GRAY	SNA
CIS	BN39-00244E	CBF SIGNAL	GY17LS,15P/15P,20276-N,1830mm,UL20276,BLACK,D-SUB/MALE,CORE:220mm,DET. TYPE	
CIS	BN39-00409A	LEAD CONNECTOR	GY17VS,30AWG*1PR,UL/CSA,30P,135mm,#30,12507HS-30W,1615B-30,BK,CABLE CLAMP	
CIS	BN63-00568A	COVER-STAND	GOYA17(173V),ABS HB,WH11	SNA
CIS	BN63-00571A	SHIELD-PCB	GOYA17(173V),SPTE,T0.8	SNA
PI/PCB+SH/BRKT	6003-000117	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA
SH/BRKT+PAN	6001-001692	SCREW-MACHINE	BH,+,M3,L3,ZPC(YEL),SWRCH18A,FP,-	
SH/COV+FUN/WIRE	6003-000117	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA
SH/COV+PAN	6001-000131	SCREW-MACHINE	BH,+,M3,L6,ZPC(YEL),SM20C,-	SNA
SH/D_SUB+SH/COV	6003-000269	SCREW-TAPTITE	BH,+,S,M3,L6,ZPC(YEL),SWRCH18A	SNA
CIS	BN96-00338A	ASSY MISC P-SHIELD COVER	GOYA173V,,,SECC T1.0	SNA
CIS	BH68-30003B	LABEL-HIGH VOLTAGE	CKA4217(C),ART,100G,YEL,BLK,W30*L30,CDT-TUBE	SNA
CIS	BN61-00709A	BRACKET-SUPPORTI(SHIELD)	GY17VS,SECC,T0.8	SNA

Loc. No.	Code No.	Description	Specification	Remarks
CIS	BN63-00570A	SHIELD-COVER	GOYA17(173V),SECC ,T1.0	SNA
CIS	BN71-00022A	EARTH PLATE	RB15AS,SUS,T0.15	SNA
-	BN91-00747Y	ASSY CHASSIS	GG15LS	
ADT	BN44-00082A	ADAPTOR-INVERTER	FSP048-3PI01,17 GOYA,110V/230VAC,50/60HZ,+13V/+5V/+3.3V,2.5A/1.5A/0.3A,48W,110/	
CIS	BN96-00671A	ASSY MISC P-SHIELD SUB	GY17VS,SECC T0.5	SNA
CIS	BN61-00708A	BRACKET-SUPPORT(D_SUB)	GY17VS,SECC,T0.8	SNA
CIS	BN63-00574A	SHIELD-D SUB	GOYA17(173V),SPTE,T0.5	SNA
-	BN92-00696F	ASSY LABEL	GY17VSSS,ADC,UNITED STATES	SNA
CIS	BN68-00404B	LABEL RATING	GH17MS,SS,PE,T0.05,90,45,BLK,POLYESTER,,GY17M*	SNA
-	BN92-00711A	ASSY P/MATERIAL	GY17VS,,,,	SNA
P/M	0203-001100	TAPE-OPP MASKING	OPP/W75/CLR,T0.05,W75,L800000,CLR	SNA
P/M	6902-000111	BAG PE	HDPE,T0.015,L800,W650,TRP,28,4,PE MARK	SNA
P/M	6902-000379	BAG AIR	HDPE,T0.2,L1800,W1000,TRP,,,PAPER	SNA
P/M	BH69-00256A	PAD-PACKING-EDGE	MV540,B400,200,2170,-,-,YEL,-,-	SNA
P/M	BH69-00457A	PACKING-PAD	GH17,FOAM,T3.0,1180,1130	SNA
P/M	BH69-40308A	PALLET-PACKING	GH15LS,WOOD,-,-,W1390,L916,H120,-,-,-	SNA
P/M	BH69-40375A	PAD-TOP	SW4,W900*L830*H4,LXA410TLMU	SNA
P/M	BH69-40379A	PACKING-WRAP	LDPE,W500*T0.02,-,-	SNA
P/M	BN68-00129A	LABEL SHIPPING	-,LABEL SHIPPING,ART-PAPER,100G,-,WHT,BLACK,-,-,-	SNA
P/M	BN69-00140T	PAD-PALLET COVER	SUN(LSA810),SW,900,3760,-,-,-,-,-	SNA
P/M	BN69-00493A	CUSHION-T/B	GY17VS,EPS,,,,,,,M50	SNA
-	BN92-00741V	ASSY BOX	GY17VSSN/XSJ,SEJ,JAPAN	SNA
CIS	BH68-00329C	LABEL BAR CODE	-,ALL,TCO99,DOMESTIC,ART-PAPER 90G,-,WHT,BLACK,-,-,-	SNA
CIS	BH68-20306A	LABEL-SERIAL	-,ART,100G,-,-,-,-,-,-,-	SNA
CIS	BH68-70355A	CARD-WARRANTY,CASE	CSK5577J/LR,SEJ,JAPAN,-,-,J,-	SNA
CIS	BH68-70431A	CARD-WARRANTY	SAMSUNG 400TFT,SEJ,JAPAN,MOJO,	SNA
CIS	BH75-10529C	UNIT-HANDLE/PACKING	S/M170MP,PE-LD,PE-HD,-,WHITE,-	
CIS	BN72-60001A	LEVER-TOP	LSD210TL,PE-LD,WHITE,TFT_LCD	SNA
CIS	BN72-60002C	LEVER-BOTTOM	S/M170MP,PE-HD,BLUE	SNA
CIS	BN69-00508G	BOX	S/M173V,JAPAN,CB-SW4,YEL,A-1,L448*W442*H176	SNA
-	BN92-00761G	ASSY ACCESSORY	GY15VSSN/XSJ,SEJ,JAPAN	SNA
CIS	BN96-00497G	ASSY ACCESSORY	GY15VSSN/XSJ,SEJ,JAPAN	
CIS	0203-000214	TAPE-OPP MASKING	OPP/W50/CLR,T0.05,W50,L400000,	SNA
CIS	3721-001007	PLUG-CONVERSION	2P,-,-,-	
CIS	6902-000110	BAG PE	LDPE,T0.05,L356,W240,TRP,28,2,PE MARK	SNA
CIS	BH39-10339T	CBF POWER CORD	DET,VCTF,125V/7A,BLK,1800MM,TA	
CIS	BH59-00179A	S/W DRIVER-3.4	ALL,NATURA-COLOR,ALL,-	SNA
CIS	BH68-00021A	CARD-TCO99-02	TCO99,SAMSUNG,EXPORT,ART120G,-,148X210,ENGLISH	SNA
CIS	BH68-00297G	MANUAL-ETC-00	WIN2000,SAMSUNG,English,W/W,MIMOJO80G,-,148,210,-,-,-,-	SNA
CIS	BH68-00522A	MANUAL USERS-00	P/CORD SETUP GUIDE,SYNCMASTER,EN,W/W,MOJO100G,250,250,00	SNA
CIS	BN68-00414A	MANUAL USERS	153V,173V,193V,SyncMaster,Japanese,Japan,00	SNA
-	DG-GY17VSSW/XSJ	3	HT17E12(ZPD)	-